

MATTEL CARTRIDGE CONNECTOR

<u>SIGNAL</u>	<u>ORIGIN.</u>	<u>NO. OF LEADS</u>	<u>INPUT/OUTPUT</u>
DBO-DB 15	CP1610	10	I/O
* BUS CNTRL. OUT	CP1610	3	0
* BUS CNTRL. IN	CART.	3	I
* SR1	8900	1	0
* INTRIM	CART.	1	I
* SR2	8900	1	0
* BUSRQ	CART.	1	I
* BUSAK	CP1600	1	0
* SST	CART.	1	0
MSYNC	8900	1	0
MCLK	8915	1	0
AUDIO	CART.	1	I
VIDEO	CART.	1	I
CBLNK	8900	1	0
INTR	CART.	1	I
RESET	CART.	1	I
+5	P.S.	1	0
GND	P.S.	6	0

* These signal pairs are looped through the ROM cartridge.



MICROELECTRONICS DIVISION
 GENERAL INSTRUMENT CORP.
 HICKSVILLE, NEW YORK 11802

SPECIFICATION NO.

DRAWING NO. 39-149

REV.

SHEET 1 of 1

B

Form IE102
 KG 9/26/78